

## CX1800.1 Mono Amplifier

The CX 1800.1 Mono Amplifier is built for big bass in a sleek, yet affordable package.

Using a Class D power plant and FIT™ (Failsafe Integration Technology) for superior dependability, this amp features a variable bass boost with KickEQ™, giving you as much as a 12dB of extra bump with a simple turn of the optional CXRC Remote Bass Controller. A powerful 12dB crossover and 24dB subsonic filter is included, letting you quickly tune your system to perfection. Use the full range outputs to expand your system with other bass amps, or a full range amp to complete your system.

This CX amplifier delivers as much as 1800 watts into one channel. See below for more details.



## Specifications

### MODEL

CX-SERIES MONOBLOCK  
AMPLIFIERS CXA1800.1

### Power (watts/ch), 2 Ohm stereo

-

### Power (watts/ch), 4 Ohm bridged mono

900x1

### Power (watts/ch), 2 Ohm mono

1800x1

### CXRC Remote Bass Capable (sold sep.)

yes

### Dimensions

(in.) 2-3/8H x 7-3/16W x 13-5/8

(cm) 6.0H x 18.0W x 34.5

### Frequency Response (Hz):

25-200, +0/-1dB

### Input Sensitivity:

high level 250mV-10V,

low level 125mV-5V

### Signal-to-Noise Ratio:

>95dB, a-weighted, re: rated power

### Active Crossover:

12dB/octave, variable 50-200Hz, low pass only

### Subsonic Filter

24dB/octave high-pass fixed @ 25Hz

### KickEQ™ Boost

variable to +12dB, centered @ 40Hz