

CX300.4 Multi-Channel Amplifier

The CX 300.4 Four-Channel Amplifier is built to power all your door speakers in a small, powerful package.

Using a Class AB power plant, this amp features a variable bass boost with KickEQ™, giving you as much as a 12dB of extra bump. A powerful 12dB crossover is included, letting you quickly tune your system to perfection. Use the full range outputs to expand your system with a full range amp to complete your system.

This CX amplifier delivers as much as 75 watts per channel (4 channels driven), or 150 watts into two sets of bridged channels. See below for more details.



Specifications

MODEL

CX-SERIES MULTI-CHANNEL
AMPLIFIERS CXA300.4

Power (watts/ch), 2 Ohm stereo

75x 4

Power (watts/ch), 4 Ohm bridged mono

150 x 2

Power (watts/ch), 2 Ohm mono

--

CXRC Remote Bass Capable (sold sep.)

yes

Dimensions

(in.) 2-3/8H x 7-3/16W x 12-7/16

(cm) 6.0H x 18.0W x 32

Frequency Response (Hz):

10-20k, +0/-1dB

Input Sensitivity:

high level 250mV-10V,
low level 125mV-5V

Signal-to-Noise Ratio:

>95dB, a-weighted, re: rated power

Active Crossover:

12dB/octave, variable 50-200Hz, selectable
high pass, low pass or all pass

Subsonic Filter

N/A

KickEQ™ Boost

variable to +12dB, centered @ 40Hz