

KAC-M1824BT



Compact Bluetooth 4 Channel Digital Amplifier

KAC-M1824BT



MAX POWER
400w

CONFORMAL
Coating

SPEAKER
Level Input

CLASS
D

IPX5
REMOTE
CONTROL



General Features

Signal to Noise Ratio: 90 dB
RMS POWER Output 4Ω: 45W x 4
RMS POWER Output 2Ω: 45W x 4
RMS POWER Output Bridged: 90W x 2
Dimensions(WxHxD): 5-11/16" x 1-3/4" x 3-7/8"
Singal Sensing Turn-on

BUILT-IN BLUETOOTH

With today's smartphones hosting a wide variety of listening choices such as stored music, internet radio, podcasts, etc., it is no wonder that customers want to use this as their primary listening source. Bluetooth offers the easiest and most popular connection, KAC-M1824BT is not only your standalone Bluetooth gateway but if used with an in-dash receiver, it will double the power of a typical CD receiver with it's built-in 45Watts x 4 of amplification. A water resistant controller can be used to adjust volume and change tracks.



For classic car

<https://www.kenwood.com/usa/car/marine/kac-m1824bt/>