

# KAC-M3004



Compact 4-Channel Digital Amplifier

KAC-M3004

MAX POWER  
600w

CONFORMAL  
Coating

SPEAKER  
Level Input

CLASS  
D

Variable  
LOW-PASS  
HIGH-PASS  
Filter

## General Features

RMS POWER Output 4Ω: 50W x 4  
RMS POWER Output 2Ω: 75W x 4  
RMS POWER Output Bridged: 150W x 2  
Dimensions(WxHxD): 6-1/2" x 1-3/4" x 3-7/8"  
Signal Sensing Turn-on  
Conformal Coating \*1

<http://www.kenwood.com/usa/car/amplifiers/kac-m3004/>